

Legal Notices

This manual and any examples contained herein are provided "as is". JNC makes no warranty of any kind with regard to this manual, including, but not limited to, the implied warranties of merchantability, non-infringement and fitness for a particular purpose. JNC shall not be liable for any errors or for incidental or consequential damages in connection with the furnishing, performance, or use of this manual or the examples contained herein.

Reproduction, adaptation or translation of this manual is prohibited without prior written permission of JNC Service B.V.

CAUTION: This Quick Reference Guide may be revised or withdrawn at any time without prior notice.

This document provides basic usage instructions and information on setting up your DOKKi docking station.

UNPACKING



Do NOT use a knife to open the package or contents as this may result in damage to the product(s)

Open the outer box on the top-side (indicated by the 'this way up' sign on the labels). Take the CPN-30 from its box and carefully remove the bubble-foil.

REMOVING THE TRANSPORT TAPE

The five trays have been secured with special orange tape on both sides, to prevent them from moving during transport.

Locate and remove all the orange tape gently while holding each tray as you remove the tape. Verify afterwards that these parts are in their original operational position. If not, re-fit as necessary.



Orange transport tape

BOX CONTENTS

- CPN-30 docking station

Promotional items aren't listed here.



DOKKi CPN-30

 FITS
OPN3002i
OPN3002n
OPN4000i
OPN4000n

The CPN-30 will fit Opticon scanner models OPN-3002i, OPN-3002n, OPN-4000i and OPN-4000n.

The insertion area is as tight as possible to ensure stability for the scanner. This also means that the scanner won't fit when used in combination with any available sleeve or case (rubber, leather, etc.).

Always check our website for the latest list of models that fit if your model isn't listed here.



Before inserting any scanner in the dock be sure to remove the USB cover (see note below).

Save the USB cover in case it's needed at a later stage.



By removing the USB cover from the scanner dust and/or moist can penetrate the connector and opening(s) behind the USB cover more easily. It is possible that the products' IP rating has been altered too. Removing any original part from the scanner could void warranty. Doing so is at your own risk!

POSITIONING

The CPN-30 has rubber feet on the bottom and can be used as a **desk-stand**, or it can be **wall-mounted** with the 'Wall Mount KIT' which is separately available as an accessory.

Desk-stand

Please make sure the CPN-30 is positioned on a firm background which is level.

Wall-mounted

This Wall Mounting KIT is identical to the CMT-30 mounting kit and is separately available as an accessory.

The CMT-30 / CPN-30 Wall Mounting KIT consists of:

- CMT-30 Mount Instruction
- CMT-30 Drill Template 1:1 scale (A3 format)
- M6 x 35mm universal nylon plugs, gray (3x)
- M5 x 40mm screws, galvanized (3x)

POWER AND CONNECTION

Input: 100–240V~, 50/60Hz

After unpacking and positioning, simply plug the power connector (type: Shuko F) in the wall outlet. The CPN-30 is now ready for use.



CPN-30 rear view

DOCKING YOUR SCANNER

Hold the scanner between your thumb and index finger near the scanwindow on the OPN's body with the USB connection facing down. Simply connect your OPN scanner to the docking station by gently placing the OPN over the CPN to align the connectors. When aligned press the scanner down to secure the connection.



Press firmly but never use excessive force when pressing down as this might damage the connectors!
Always check for obstructions on both connectors before trying to dock the scanner.



docking of the OPN-3002 series



docking of the OPN-4000 series

ACCESSORIES

- Wall Mount Kit to securely mount the CMT-30 to a wall

Check our website for the latest available accessories.

TROUBLESHOOTING

If you are experiencing any problem with the CPN-30 the first thing to check is if the scanner operates correctly when connected directly to the PC with an USB cable. Do so by plugging the USB cable that came with your scanner into your scanner and make sure the other end of the USB cable goes directly into the PC (bypassing any present HUB).

If it does function properly continue at the check-list below, otherwise the problem is with your scanner itself, the USB cable or the PC (USB port and/or driver(s)).

Checklist

No power *1	<ul style="list-style-type: none"> - Is the mains power operational and connected properly? - Is the scanner firmly pressed into the docking station? - Does the scanner operate in other ports of the dock? (*2)
No communication *1, *2	<ul style="list-style-type: none"> - Is the scanner fully charged? - Are the necessary scanner drivers properly installed? - Do the communication settings match between scanner and the PC? - Are there no other programs polling on the same COM-port?
*1 (and if connected to a powered USB hub)	<ul style="list-style-type: none"> - Is the power-supply of the USB hub plugged in? - Is one port on the USB hub failing, or are all ports faulty? - Is the USB cable securely fitted on both ends?
*2	If applicable to this DOKKi model

If you have any questions regarding the use of the DOKKi.eu CPN-30 docking station please contact your dealer.

BY OPENING THE PACKAGE OF THIS PRODUCT YOU AGREE TO BECOME BOUND
BY THE LIABILITY AND WARRANTY CONDITIONS.

Limited Warranty, Liability and Disclaimers

This Limited Warranty and Disclaimer extends only to products purchased directly from DOKKi.eu or a DOKKi.eu Authorized Dealer as stated on our website (<http://www.dokki.eu/dealers>).

Under no circumstance JNC will be liable for any direct, indirect, incidental, special, consequential, punitive, or exemplary damages, including but not limited to, damages for loss of profits, revenue, income, goodwill, use, data, or other intangible losses that arise from use or inability to use the CPN-30, even if JNC has been informed about the possibility of such damages.

The DOKKi.eu CPN-30 is warranted for a period of one year after purchase, covering defects in material and workmanship. JNC will repair or, at its opinion, replace products that prove to be defective in material or workmanship under proper use during the warranty period. The warranty does not apply to defects resulting from (a) improper or inadequate maintenance measures taken; (b) interfacing parts or supplies not supplied or authorised by JNC; (c) unauthorized modification or misuse; (d) operation outside the applicable environmental parameter limits specified for the product; or (e) improper site preparation or maintenance for installation.

Outside The Netherlands, return the product to your dealer. Follow the instructions provided by your dealer.